

8-bit character enable odd verify

ComPortSpeed: 2400

Data	xxxx B	xxxx B				
0	0011	LCD(1)	0-4			
1	0011	LCD(2)	0-9			
2	0011	LCD(3)	0-9			
3	0011	LCD(4)	0-9			
4	0011	LCD(5)	0-9	4000 counts is 'A'		
5	0011	Range				
6	0011	Function				
7	0011	STATE_ACDC	0000:OFF	0001:AC	0010:DC	0011:AC+DC
8	0011	+/- STATE_ATUO	0xxx:+	1xxx:-	x000:OFF	x001:AUTO x010:Manual
9	0x0D					
10	0x0A					

Function	Range
0 AC_mV	Range 0: 400mV
1 DCV	Range 1: 4V 2:40V 3:400V 4:1000V
2 ACV	Range 1: 4V 2:40V 3:400V 4:750V
3 DC_mV	Range 0: 400mV
4 Ohm	Range 1:400 2:4k 3:40k 4:400k 5:4M 6: 40M
5 C	Range 1:40n 2:400n 3:4u 4:40u 5:400u 6: 4m 7:40m
6	Range 0: 1000
7 uA	Range 0:400u 1:4000u
8 mA	Range 0:40m 1:400m
9 10A	Range 0: 10
10 Fm	Range 0:
11 Diode	Range 0:
12 Hz	Range 0:40 1:400 2:4k 3:40k 4:400k 5: 4M 6:40M 7:400M
13	Range 0: 1832
14 Unspecified	
15 %(4-20mA)	Range 0: